

# Induction cooker model 7000

239346

Stainless steel housing with two hobs. Front hob has a maximum power of 5000 W, when the front hob operates at 5000 W the rear hob can only generate 2000 W. Rear hob has a maximum power of 3500 W only while the front hob doesn't exceed 3500 W. Electronic protection against overheating. With adjustable metal feet and removable air filter. Works on 380 V, supplied without plug, an electrician is required for the installation. Suitable for pans with bottom diameter between 140 and 280 mm. Maximum load of the induction cooker: 20+20 kg.



## Specifications

Usage area	: Indoor, Kitchen
Voltage	: 400
Unit temperature	: Celsius
Heating element	: Induction
Protections	: Overheat protection
Electrician needed	: Yes
Materials	: Stainless steel

Packed per	: 1
Packaging type	: Box
Length (mm)	: 405
Width (mm)	: 698
Height (mm)	: 145
Power (input) (W)	: 7000
Programmable	: No
Measurements	: 405x698x(H)145

## Transport specifications

EAN	: 8711369239346
Intrastat code	: 84198180
Gross weight (kg)	: 19.73
Net weight (kg)	: 16.93
Sales units per pallet	: 18
Plastic packaging (gram)	: 393

### HENDI B.V.

Innovatielaan 6  
6745 XW De Klomp, The Netherlands  
T: +31 (0)317 681 040  
E: info@hendi.eu

### HENDI Polska Sp. z o.o.

ul. Firmowa 12  
62-023 Robakowo, Poland  
T: +48 61 6587000  
E: info@hendi.pl

### HENDI GmbH

Ehring 15  
5112 Lamprechtshausen, Austria  
T: +43 (0) 6274 200 10 0  
E: office.austria@hendi.eu

### HENDI S.R.L.

Str. 13 decembrie 94A, Hala 14  
Braşov, 500164, Romania  
T: +40 268 320330  
E: office@hendi.ro

### PKS HENDI South East Europe SA

5 Metsovou Str.  
18346 Moschato, Athens, Greece  
T: +30 210 4839700  
E: info@pks-hendi.com

### HENDI Italia S.R.L.

Via Leonardo da Vinci 4  
39100 Bolzano (BZ), Italy  
T: 800 727 438  
E: office.italy@hendi.eu