

Sound level meter SAUTER SU







Professional sound level meter

Features

- Professional sound level meter for measuring noise in areas such as, environment, mechanical applications, car industry and much more
- Measures the sound intensity in the workplace
- Helps in differentiating between normal noise influences, and excessive noise, nuisances e.g. in a production hall
- 11 Data interface RS-232, included
- 2 Delivered in a robust carrying case
- Multi measuring functions:
- Lp: Standard sound level measuring function
- Leq: Energy equivalent sound level measuring mode (type A)
- Ln: Shows the deviation from a pre-defined limit in %
- Selectable methods of evaluation:
- A: As sensitive as the human ear
- C: Sensitive for noisier environmental conditions, where there are machines, plant, motors etc.
- F: For areas with constant sound intensity

- Limit value function: programmable value for the maximum level value
- Track function for continuous recording of changing environmental conditions
- Peak Hold Mode to capture peaks
- Internal memory for 30 measured values, transferable to PC with SAUTER ATC-01

Technical data

- Measuring precision: 3 % of [Max]
- Dimensions W×D×H 236×63×26 mm
- Battery operation, batteries standard 4× 1.5 V AAA
- Net weight approx. 170 g

Accessories

- Data transfer software, interface cable included, SAUTER ATC-01
- Adjustment device for regular adjustment of the sound level meter, SAUTER ASU-01
- Foam windshield, SAUTER ASU-02

STANDARD

















Model	Туре	Measuring range	Readout	
SAUTER		[Max] dB	[d] dB	
	Lp A	30-130		
SU 130	Lp C	35-130	0,1	
	Lp F	35-130		

SAUTER CATALOGUE 2021



Pictograms



Adjusting program (CAL):

For quick setting of the instrument's accuracy. External adjusting weight required



Calibration block:

Standard for adjusting or correcting the measuring device



Peak hold function:

Capturing a peak value within a measuring process



Scan mode:

Continuous capture and display of measurements



Push and Pull:

The measuring device can capture tension and compression forces



Length measurement:

Captures the geometric dimensions of a test object or the movement during a test process



Focus function:

Increases the measuring accuracy of a device within a defined measuring range



Internal memory:

To save measurements in the device memory



Data interface RS-232:

Bidirectional, for connection of printer and PC



Profibus:

For transmitting data, e.g. between scales, measuring cells, controllers and peripheral devices over long distances. Suitable for safe, fast, fault-tolerant data transmission. Less susceptible to magnetic interference.



Profinet:

Enables efficient data exchange between decentralised peripheral devices (balances, measuring cells, measuring instruments etc.) and a control unit (controller). Especially advantageous when exchanging complex measured values, device, diagnostic and process information. Savings potential through shorter commissioning times and device integration possible



Data interface USB:

To connect the measuring instrument to a printer, PC or other peripheral devices



Bluetooth* data interface:

To transfer data from the balance/measuring instrument to a printer, PC or other peripherals



((((:•

IR

SWITCH

ANALOG

STATISTIC

KCP

valves, etc.

Analogue interface:

Analog output:

4 mA - 20 mA) Statistics:

PC Software:

Printer:

WLAN data interface:

Data interface Infrared:

To connect relays, signal lamps,

To transfer data from the balance/measuring instrument to a printer, PC or other peripherals

To transfer data from the measuring instrument

to a printer, PC or other peripheral devices

Control outputs (optocoupler, digital I/O):

To connect a suitable peripheral device for

analogue processing of the measurements

For output of an electrical signal depending

Using the saved values, the device

calculates statistical data, such as

To transfer the measurement data

to print out the measurement data

from the device to a PC

Network interface:

to an Ethernet network

digital systems

Measuring units:

GLP/ISO record keeping:

average value, standard deviation etc.

A printer can be connected to the device

For connecting the scale/measuring instrument

It is a standardized interface command set for

KERN balances and other instruments, which

parameters and functions of the device. KERN

devices featuring KCP are thus easily integrated

with computers, industrial controllers and other

allows retrieving and controlling all relevant

Of measurement data with date, time and


serial number. Only with SAUTER printers

Weighing units can be switched to e.g.

non-metric at the touch of a key. Please

KERN Communication Protocol (KCP):

on the load (e.g. voltage 0 V - 10 V or current





Protection against dust and water

splashes IPxx:

The type of protection is shown in the pictogram.



Resets the display to "0"



Battery operation:

Ready for battery operation. The battery type is specified for each device



Rechargeable battery pack:

Rechargeable set



Mains adapter:

230V/50Hz in standard version for EU. On request GB, AUS or USA version available



Power supply:

Integrated, 230V/50Hz in EU. More standards e.g. GB, AUS or USA on request



Motorised drive:

The mechanical movement is carried out by a electric motor



Motorised drive:

The mechanical movement is carried out by a synchronous motor (stepper)



Fast-Move:

The total length of travel can be covered by a single lever movement



Verification possible:

The time required for verification is specified in the pictogram



DAkkS calibration possible:

The time required for DAkkS calibration is shown in days in the pictogram



Factory calibration: The time required for factory calibration is specified in the pictogram



Package shipment:

The time required for internal shipping preparations is shown in days in the pictogram



Pallet shipment:

The time required for internal shipping preparations is shown in days in the pictogram



PRINTER

refer to website for more details Measuring with tolerance range (limit-setting function):

Upper and lower limiting can be programmed individually. The process is supported by an audible or visual signal, see the relevant model

Your KERN specialist dealer:

^{*}The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by KERN & SOHN GmbH is under license. Other trademarks and trade names are those of their respective owners.